

PEARSON™ CURRENT MONITOR MODEL 8546



Sensitivity	1 Volt/Ampere $\pm 1\%$
Output resistance	1500 Ohms
Maximum peak current	500 Amperes
Maximum rms current	50 Amperes
Droop rate	10 %/millisecond
Useable rise time	0.6 microsecond
Current time product	0.15 Ampere-second max.
Low frequency 3dB point	15 Hz
High frequency 3dB point	500 kHz
I/f figure	0.8 rms Amperes/Hz
Output connector	BNC
Operating temperature	0 to 65°C
Weight	3.7 pounds

© 2008 Pearson Electronics, Inc. 8546.wpd 080916

